Specification Page

Effective: 12-15-2006 Bulletin #: spcts2006.01



CTS – Inline Filters

	CTS-2	CTS-3	CTS-4C	CTS-4B	CTS-6	CTS-8	CTS-10
Specifications							
Connection Size & Type	2" NPT	3" NPT	4" / flanged	4" / flanged	6" / flanged	8" / flanged	10" / flanged
Max Pressure (PSI)	125	125	125	125	150	150	150
Max Flow Rate (GPM)	100	200	350	350	750	1300	2000
Lid Type	clamp	clamp	clamp	Bolted	bolted	bolted	bolted
Height	15 ½"	28 ¹ / ₈ "	26 ¼"	26 1/4"	36 ⁷ /16"	48 11/16"	59 ¹⁵ / ₁₆ "
Width	9 1/4"	13 ¹ /8"	19 ³ /16"	19 ³ /16"	24 ⁵ /8"	31 ½"	39 ¾"
Weight (lbs.)	14	30	60	60	125	200	400
Gauge Ports	1/4" FPT	1/4" FPT	1/4" FPT	¼" FPT	1/4" FPT	1/4" FPT	1/4" FPT
Flush Port	1 ½" NPT	1 ½" NPT	1 ½" NPT	1 ½" NPT	1 ½" NPT	1 ½" NPT	1 ½" NPT

Construction

Housing T304 stainless steel

Filter Screen frame & mesh: T304 stainless steel Internal Piping 2" and 3" models use type 304S.S. riser pipe

4" through 10" models use PVC elbow and riser pipe assembly

Gaskets EPDM lid gasket, disk gasket and filter gasket

Hardware Bolt, washer, clamp & handle: T304 stainless steel Nut: brass

Gauge Ports 1/4" gauge ports on inlet and outlet sides of screen

Filter Element Conical in shape and vertical in orientation

General

Pressure Loss – 1 psi (during maximum flow) Mesh sizes – 16 to 200 available Features a debris flush port

Automatic Flush Timer



Options

Pressure Differential Alarm Monitors the inlet and outlet system pressure. When the filter screen becomes clogged, the

pressure differential switch-gauge will trigger an audible siren and visual flashing alarm.

Debris is purged automatically using a water diaphragm valve and a timer based valve

controller. The timer controller is easy to use, water-resistant and can be powered with 9-

volt batteries or AC power.

Bypass Manifold Manifold consists of 3 flanged butterfly valves enabling water to by-pass the inline filter

during maintenance.

110/12VDC Power Supply Plugs into 110V Wall Plug

Pressure Gauges 2 required per. strainer (gauge ports included on strainer housing)